

Door Activation Devices

CM-75 V2 Series Column™ Switch

INSTALLATION INSTRUCTIONS

THIS PACKAGE INCLUDES:

- | | |
|---|-------------------------------------|
| 1 - CM-7536 V2 Column™ Switch | 4 - Concrete Anchors |
| 4 - #14 x 1-1/2" Slot Hex Head Steel Tapping Screws | 4 - 1/4-20 x 1" S/S Pan HD PH Screw |
| 4 - Nylon Anchors | 2 - Wire Nut C/W Spring |



1. GENERAL DESCRIPTION

Camden CM-75 V2 Series Column™ Switches offer a rugged and attractive ADA compliant switch design that is easy to activate from any angle, providing years of trouble-free operation. CM-7536 V2 utilizes 2 fully redundant 15 amp Form-C contact switches, and molded impact and flame resistant end caps which provide easy snap-in installation of the Lazerpoint TX-9 transmitter.

The Column™ Switch may be mounted to any flat wall surface, or to our Model CM-42 or CM-48 anodized aluminum or stainless steel bollards. We provide mounting hardware for all options.

CM-7536 V2 uses two switches which can be hardwired or fitted with either the Kinetic or Lazerpoint wireless transmitters. In the hardwired layout, they will be wired in parallel. The wireless versions can be paired with Camden Lazerpoint or Kinetic receivers.

Optional CM-7536-LED Column™ Switches are available that provide built-in LED annunciation.

2. SPECIFICATIONS

Contact Rating	15 amps @ 30 VDC
Contacts	2 x SPDT momentary. Contact switch (Form C), UL listed
Construction	Heavy duty extruded aluminium
Finish	Anodized clear, dark bronze or stainless steel
Mounting	4 x #14 wood screws or 1/4"-20 S/S machine screws with anchors
Actuator Width	3" (76mm)
Dimensions (overall)	37- 1/2" H x 5-7/8" W x 1-1/2" D (955mm x 150mm x 38mm)

3. INSTALLATION

Code Requirements: If installed according to these instructions the CM-7536 V2 Column™ switch will meet the requirements of the California Building Code (Section 1117B.6, Date: 2009), and Section 3.8.3.3.17(b) of the Ontario Building Code.




Figure 3.1 Base Unit Mounting

Installation Steps:

1. Remove the assembled unit from packaging. The unit must be disassembled to be installed. To do this, remove the two small Phillips screws holding the top cap in place. Remove the cap. Then, grasping the center (metal) actuation bar, pull vertically until the entire actuation bar is removed from the base unit. Set the actuation bar aside and protect from surface damage.

2. Determine the optimum height from the finished floor. See illustration (above) for common height. If utilizing an in-wall electrical box, center the backplate over the box, while lining up the top edge with your mark.

3. Using a level, ensure the base unit is plumb and level, and mark the 4 mounting locations through the adjustable nylon inset screws onto the wall surface (if on drywall use a pencil, and if on concrete a narrow Sharpie or similar).

4. a) Drill the wall at the 4 marked locations, and tap in the appropriate wall plugs. We supply both drywall and concrete anchors for the included #14 screws.

4. b) If mounting the Column Switch to an aluminum post or framing section, drill and tap 4 holes for 1/4"-20 Stainless Steel Machine screws (also provided).

Note: Camden CM-42 and CM-48 series posts are available with pre-drilled and tapped holes preparation for Column™ switches.

5. a) **If hardwiring:** Use the supplied wire nuts to make your wire connections. Push excess wire into the back box and ensure cable is not exposed to the moving parts of the switch, or pinched between the back of the base unit and wall surface.

4 nylon inset screws may be turned in or out to help plump up Column™ Switch and adjust for wall irregularities. Check with a level. When satisfied, install the 4 mounting screws and tighten.

5. b) **If using Lazerpoint RF:** The cap includes a snap-in compartment for our TX-9 transmitter. Place transmitter in the cap, with the wires hanging down and to the front of the cap. Using the supplied wire nuts, connect the two activating wires to the Column™ Switch lead wires. Slide the battery and the extra wiring into the center (rear) channel provided. Do not slide all of the wire into the channel, so that the cap can hang off to one side while you perform the next step.

Using the supplied wire nuts, connect the two activating wires to the Column™ Switch lead wires. Then, slide the battery and the extra wiring into the center (rear) channel provided. Do not slide all of the wire into the channel, so that the cap can hang off to one side while you perform the next step.

5. c) **If using Kinetic RF:** The CM-7536K uses 2 Kinetic RF switches installed near the top and the bottom of the actuator. When pairing this switch with a Kinetic receiver, you must pair both the top and the bottom switches. The pairing of Camden Kinetic transmitters is detailed in the CM-RX90v2 installation manual.

5. d) **If using other RF:** Using the supplied wire nuts, make your wire connections to the RF transmitter and tuck the transmitter and excess wire into the back box (or wall cavity). Ensure cable is not exposed to the moving parts of the switch, or pinched between the back of the base unit and the surface of the wall.

6. Reassemble the (center) actuation bar into base unit. This is done by holding the hanger (located at the top center) vertically 'up' – then carefully sliding actuation bar down the length of the base unit, being careful not to bend or break the springs or internal switches.

When the bottom edge of the actuation bar reaches the height of the springs, use your free hand to tuck in the spring and switches under the actuation bar as it slides over them. When activation bar is approx 2" from bottom, position hanger so it falls into the slots provided at the top of the base unit. Slide actuation bar down until it rests on the hanger. Actuation bar should now move freely within the base unit. Test the operation of the switch before mounting the cap.

7. When satisfied with the switch operation, place cap back on top, and screw in the two small self-tapping Phillips screws.




Figure 3.2 Lazerpoint RF

4. KINETIC WITH COLUMN™ SWITCH AND MOUNTING AGAINST WALL




Figure 4.1 CM-7536 V2 with Kinetic - Wall Mounting

5. FCC COMPLIANCE INFORMATION

(If using Kinetic by Camden™)

FCC ID: 2A4GFAGIM5002

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

1. This device may not cause harmful interference, and
2. This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be

determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Changes or modifications not expressly approved by manufacturer could void the user's authority to operate the equipment.

IC: 1105A-AFIM5002

This device complies with Industry Canada licence-exempt RSS standards. Operation is subject to the following two conditions:

1. This device may not cause interference, and
2. This device must accept any interference, including interference that may cause undesired operation of the device.

6. CM-7536 & CM-7536-LED V2 DIMENSIONS

Figure 6.1 CM-7536 V2 Dimensions







Figure 6.2 CM-7536-LED V2 Dimensions

The Optional CM-7536-LED Column™ Switch provides a built-in LED annunciation.

It features a BiColor LED (Red/Green) built into the Column™ Switch rated at ≤ 20mA @ 12 to 24 VDC.



7. SYSTEM INSPECTION

After the Installation and operational check of the system:

1. Place any applicable labels on the door (as per ANSI A156.10 or A156.19 guidelines).
2. Instruct the owner on door system operation and how to test it. This should be checked on a daily basis.
3. Strongly recommend to the owner that the complete entry be inspected twice a year as part of the service agreement.

8. WARRANTY

Camden Door Controls guarantees the CM-75 V2 series to be free from manufacturing defects for 3 years from date of sale. If during the first 3 years the Column™ switch fails to perform correctly, it may be returned to our factory where it will be repaired or replaced (at our discretion) without charge. Except as stated herein, Camden extends no warranties expressed or implied regarding function, performance or service.

9. PARTS INFORMATION

Item	Parts Description	QTY
1	CM-7536 Actuator	1
2	CM-7536 Base	1
3	#4 x 1/2" FH Phillips S/S Tapping Screw	2
4	CM-7536 Black Nylon End Cap	2
5	SPDT Switch	2
6	12" Wire Harness	1
7	9" Wire Harness	1
8	S/S 4lbs Comp. Spring	2
9	Nylon Screw	4
10	Rubber Bumper	3
11	Edging Grommet	4
12	Nylon Washer	4
13	Wire Nut C/W Spring	6
14	#14 x 1-1/2" Slot Hex Head Tapping Screws	4
15	Nylon Anchor Plugs 10 - 14 Screw x 1-9/16"	4
16	1/4"-20 Machine Screws	4
17	BiColor LED (Option)	1




Figure 9.1 Exploded View

CM-75 V2 SERIES COLUMN™ SWITCH

INSTALLATION INSTRUCTIONS

ORDERING INFORMATION FOR REPLACEMENT PARTS

Part Number	Description
60-42F022	7536 (Version 2) Black Nylon End Cap
60-73021-G	BiColor 22mm Flat LED Red/Grn with Harness
60-73C021-B	Replacement CM-74/75 LED Blue
60-34B109	#87 Parts Kit for 7436 & 7536 Series (Version 2)

ORDERING INFORMATION FOR COLUMN SWITCH OPTIONS

Part Number	Description
CM-7536/4FE	36x6 COLUMN Push Plate Sw. Alum. WC, PTO & PPO
CM-7536/4F	36x6 COLUMN Push Plate Sw. Alum. WC & 'PPO'
CM-7536/4	36x6 COLUMN Push Plate Sw. Alum. WC & 'PTO'
CM-7536/8BFE	36x6 COLUMN Push Plate, Alum. Lock Icon, PTL/PPV
CM-7536/8BF	36x6 COLUMN Push Plate, Alum. Lock Icon & PPV
CM-7536/8B	36x6 COLUMN Push Plate, Alum. Lock Icon & PTL

ORDERING INFORMATION FOR COLUMN SWITCH (WITH LED) OPTIONS

Part Number	Description
CM-7536/4FE-LED	36x6 COLUMN Push Plate Sw. Alum. WC, PTO & PPO, GRN/RD LED
CM-7536/4F-LED	36x6 COLUMN Push Plate Sw. Alum. WC & 'PPO' Green/Red LED
CM-7536/4-LED	36x6 COLUMN Push Plate Sw. Alum. WC & 'PTO' Green/Red LED
CM-7536/8BFE-LED	36x6 COLUMN Push Plate, Alum. Lock Icon, PTL/PPV, GRN/RD LED
CM-7536/8BF-LED	36x6 COLUMN Push Plate, Alum. Lock Icon & PPV, Green/Red LED
CM-7536/8B-LED	36x6 COLUMN Push Plate, Alum. Lock Icon & PTL, Green/Red LED